

Uninterruptible Power Supply (UPS) UPS Battery Enclosures



VaultFlex[™] Uninterruptible Power Supply (UPS) enclosures provide a secure, thermally managed environment that maximizes the life and performance of UPS batteries with minimal lifecycle operating expense (OpEx).

Outdoor rated construction provides the flexibility to take UPS batteries outside in order to free up space inside the data center for additional revenue-generating equipment. VaultFlex enclosures can also be mounted adjacent to modular, containerized UPS systems. Users can even opt to keep their batteries indoors, within the thermally-managed VaultFlex enclosure and raise the temperature of the data center room. This can result in significant utility savings while still maintaining optimal battery temperatures.

Features and Benefits

- Free up space in your data center by placing your UPS batteries outside
- Keep your batteries at optimal temperature even in containerized UPS applications
- Supports 480V and 384V strings of EnerSys[®] DataSafe[®] XE batteries
- Optional center tap cabling
- EnerSys service and installation available





Exterior

- Cabinet 0.080" (2mm) aluminum
- Battery rack(s) steel construction
- Finish ultra light gray polyester powder coat
- Insulation on cabinet walls and roof

Door/Side/Top Panels

- Doors front door(s)
- Door handles pad-lockable
- Door hinges hidden hinges

Cable Entry

• Ingress/Egress - cable entry plates with covers

Mounting Options

Pad mountable or optional galvanized steel plinth

Interior


Climate unit alarm400A, 500A and 600A breaker options

Standards


- IBC (2015), ASCE 7-10, CBC (2016)
- OSHPD Optional Certification

Exterior Dimsions (W / D / H) (in / mm)	DataSafe® Batteries Supported	Thermal Management
67.4″ x 34.3″ x 75.2″ 1712 x 870 x 1909	480V and 384V Strings: 12XE1150F-FR 12XE1110F-FR 12XE1010F-FR	-48VDC Heating and Air Conditioning


1.5 [38]




FRONT VIEW



FRONT VIEW DOOR REMOVED






TOP VIEW MOUNTING DIMENSIONS




RIGHT VIEW



00.0

LEFT VIEW



PLINTH MOUNTING DIMENSIONS

NOTE: All measurements are show in inches [millimeters]



EnerSys World Headquarters 2366 Bernville Road, Reading, PA 19605, USA Tel: +1-610-208-1991 / +1-800-538-3627 EnerSys EMEA EH Europe GmbH, Baarerstrasse 18, 6300 Zug, Switzerland Tel: +41 44 215 7410 EnerSys Asia 152 Beach Road, Gateway East Building #11-03, Singapore 189721 Tel: +65 6508 1780 © 2016 EnerSys. All rights reserved. Tademarks and logos are the property of EnerSys and its affiliates, unless otherwise noted. Subject to rewisions without prior notes. E&0.E. Publication No: US-VF-UPS-AA - June 2016

www.enersys.com